Method and Apparatus for Measuring a Device Under Test Using an Improved

Through-Reflect-Line Measurement Calibration

Background

[01] U.S. Patent Application Ser. No. 10/294,317 filed November 14, 2002 entitled "Method and Apparatus for Performing Multiport Through-Reflect-Line Calibration and Measurement" (herein "the '317 Patent Application") teaches a method and apparatus for performing a through-reflect-line calibration with a multiple port vector network analyzer ("VNA"). The disclosed method teaches determination of ten-term error coefficients that may be used in a method disclosed in US Patent 5,434,511 (herein "the '511 Patent") to arrive at S-parameters of a device under test (herein "the DUT") with systematic errors attributable to the VNA and the multiport test set corrected out of the measured S-parameters of the DUT. In the method according to the '317 Patent Application, it is necessary to know a type of high reflect calibration standard used in the process. Also, in the method disclosed in the '317 Patent Application, if the through calibration standard used in the calibration procedure is a non-zero through, then its electrical length must be known and specified by the calibration standard manufacturer in order to fully characterize the error coefficients in

1

the calibration process. In many cases, the electrical length of the non-zero thru is either unknown, not known to a sufficient accuracy, or is a non-repeatable value. A through calibration standard is typically unknown for on-wafer calibrations because the landing of the probe to the calibration standard is non-repeatable, which renders the electrical length also non-repeatable, and therefore, unpredictable. Even though manufacturers of coaxial calibration standards often include electrical length data, over time and after multiple uses, the electrical length can change making a calibration process that relies on the electrical length specifications, less accurate. Due to machining, process, and other non-repeatable manufacturer variations, the manufacturer specifications of the through calibration standards may not be as accurate as the calibration and measurement presumes. In addition, frequent use of the through calibration standard can cause the dimensions and, therefore, the calibration specifications to change over time while the calibration process presumes otherwise. In high frequency on-wafer measurements, a non-zero through is used exclusively. Furthermore, in an on-wafer calibration process, it is difficult to land probes repeatably on a calibration substrate to coincide with the electrical delay value provided by the calibration standard manufacturer. Any discrepancy between the actual electrical delay and the presumed electrical delay causes uncertainties in the

calibration and, therefore, the corrections made to the measurement of a device under test ("DUT"). The uncertainties are exacerbated as measurement frequencies increase.

[02] There is a need, therefore, to improve the through-reflect-line calibration process to accommodate a thru calibration standard with an unknown delay or an unknown type of high reflect calibration standard with a known phase offset.

Brief Description of the Drawings

[03] Figure 1 is a diagram of a vector network analyzer ("VNA"), switch network and signal separation devices used for measurement of a device under test ("DUT").

[04] Figure 2 shows the VNA with a reflect calibration standard connected.

[05] Figures 3 and 4 show the VNA with a line calibration standard connected and respective switch network configurations for forward and reverse measurements.

[06] Figure 5 shows the VNA with a matched load calibration standard connected.

[07] Figures 6 and 7 show the VNA with a source terminated through calibration standard connected and respective switch network configurations for forward and reverse measurements.

[08] Figures 8 and 9 show the VNA with a locally terminated through calibration standard connected and respective switch network configurations for forward and reverse measurements.

[09] Figure 10 is a flow diagram of some of the error coefficients determined in a method according to the present teachings.

[10] Figures 11 and 12 show an optional VNA measurement with a locally terminated through calibration standard connected between one of the proximal pairs of measurement ports and respective switch network configurations for forward and reverse measurements.

4

[11] Figures 13 through 17 is a flow chart of a method for calibrating and correcting S-parameters of a measured DUT according to the present teachings.

Detailed Description

[12]   US Patent No. 5,434,511 entitled "Electronic
   Microwave Calibration Device" (herein "the '511
   Patent") teaches a method for correcting measured S-
   parameters to arrive at actual S-parameters for a
   measured device. The method uses twelve error terms
   calculated from a short-open-load ("SOLT") calibration
   process. As one of ordinary skill in the art
   appreciates, a through-reflect-line ("TRL") calibration
   process is also able to determine the twelve error
   terms from which actual S-parameters are determined
   based upon measured S-parameters of a device under
   test. The twelve error terms are: (1) forward
   directivity ("EDF"), (2) forward source match ("ESF"),
   (3) forward reflection tracking ("ERF"), (4) forward
   isolation ("EXR"), (5) forward load match ("ELF"), (6)
   forward transmission tracking ("ETF"), (7) reverse
   directivity ("EDR"), (8) reverse source match ("ESR"),
   (9) reverse reflection tracking ("ERR"), (10) reverse
   isolation ("EXR"), (11) reverse load match ("ELR"), and
   (12) reverse transmission tracking ("ETR"). Because
   the isolation of the switches used in a multiport test
   set is so high, it is more accurate in most
   circumstances to ignore the forward isolation ("EXF")
   and reverse isolation ("EXR") terms and set them to
   zero. This yields a 10-term error correction process.
   The TRL calibration process is more time consuming, but

6

has the capability for more accurate measurements. More accurate measurements yield improved error terms and improved corrected S-parameters. The following discussion is directed toward multiple embodiments of an improved TRL calibration, DUT measurement, and S-parameter correction process.

[13]   With specific reference to FIGURE 1 of the drawings, there is shown a system block diagram of a 2-port VNA 200 in conjunction with a 4-port test set. The illustrated 4-port test set comprises a switch network 150 and two external signal separation devices 114_2 and 114_4, which may be used with a 2-port VNA 200 for measuring a 4-port device under test 101 (herein "the DUT"). Alternative embodiments of test sets 150 having additional switches and signal separation devices may be used for measuring DUTs having more than 4 ports. For purposes of the present disclosure, the term "vector network analyzer (VNA) 200" refers to either a two port VNA alone, a 2-port VNA with a multiport test set for calibrating and measuring devices with more than 2 ports, or a multiport VNA. Before the DUT 101 is connected, a TRL calibration process is performed to determine systematic errors to a measurement as a result of the VNA 200 and associated connections. The VNA 200 deploys first and second reference channels 201, 202, respectively, and first and second reference channel samplers 110, 210, respectively. In the test set-up shown in FIGURE 1, the samplers 110, 210 in a specific example may be bridges

7

or directional couplers. The reference channel samplers 110, 210 are placed in the first and second signal paths 107, 108 on an opposite side of a signal transfer switch 106 from signal generator 105. The samplers 110, 210 extract in one direction a small and predictable portion of the signal present on the first and second signal paths 107, 108 for measurement by the first and second reference channels 201, 202, respectively. The sampled portion is typically -10dB to -20dB for a coupler based sampler and approximately -6dB for a bridge based sampler relative to the signal level on the signal path 107 or 108. The source transfer switch 106 connects either the signal generator 105 to the first signal path 107 and a signal transfer switch terminating load 109 to the second signal path 108 or connects the signal generator 105 to the second signal path 108 and connects the signal transfer switch terminating load 109 to the first signal path 107. In a specific embodiment, there are only two switch positions for the signal transfer switch 106.

[14]   The illustrative example shown in the drawings and described herein includes a 4-port DUT 101 connected to measurement ports 103_1, 103_2, 103_3, and 103_4. The teachings herein disclose process details for calibrating ports 103_1 and 103_3. The disclosed process is repeated for all remaining ports. The present teachings may also be applied to a multiport test set-up for measuring DUTs having two or four or more device

connections. A switch network 150 permits connection
of each measurement port 103_1 through 103_{2N} to a first
or second signal path 107, 108, the transfer switch
terminating load 109, or to a local terminating
impedance, 104_1 through 104_{2N}. Certain switch network
configurations connect one of the measurement ports 103
to the first signal path 107 or/and a different one of
the measurement ports 103 to the second signal path 108
while the remaining paths are terminated in the local
terminating impedance 104. The switch network 150 also
has sampling arms 113, sampling arms 113_1 through 113_4
in the illustrated embodiment. The sampling arms 113_1
through 113_4 each comprise a sampler 114 that samples a
small and predictable portion of the signal level
present at the respective measurement port 103. The
sampler 113 may be a coupler or a bridge that takes
somewhere between −6dB and −20dB of the signal level
from the signal level present on the respective
measurement port 103. In a specific embodiment
according to the present teachings, the portion sampled
from the measurement ports 103 is substantially the
same portion sampled from the signal paths 107, 108.
The sampled signal may then be connected to either a
first or second test channel receiver 111, 112 through
a respective sampling switch 115 or may be connected to
a sampling arm terminating load 116. A switch network
150 of this configuration may connect a reflection path
from the measurement ports 103 to one of first and
second test channel receivers 111, 112 while

terminating the reflection paths from measurement ports
103 not connected to a test channel receiver in a local
sampling arm terminating impedance 116.

[15]   In an embodiment of a method according to the
present teachings, a TRL calibration on a multi-port
DUT having N device connections is performed by
conducting a 2-port TRL calibration first on each one
of N/2 direct pairs of the measurement ports 103 and if
there are more than two measurement ports, on $(N(N-2))/4$ indirect pairs of the measurement ports 103. A
user may define the N/2 direct pairs by representing
all measurement ports 103 in groupings of two
measurement ports 103, where a first port in the direct
pair is capable of connection to the first test channel
receiver 111 and a second port in the direct pair is
capable of connection to the second test channel
receiver 112. As an example, if there are N
measurement ports, the direct pairs of measurement
ports are measurement ports 103_1 and $103_{N/2+1}$,
measurement ports 103_2 and $103_{N/2+2}$, et seq. up to the
direct pair of measurement ports $103_{N/2}$ and 103_N where
measurement ports 103_1 through $103_{N/2}$ are capable of
connection to the first test channel receiver 111 and
measurement ports $103_{(N+1)/2}$ through 103_N are capable of
connection to the second test channel receiver 112.

[16]   There are $(N(N-2))/4$ indirect pairs, which are
defined as those unique groupings of two measurement
ports 103 that are not represented in the set of direct
pairs of measurement ports and where a first

10

measurement port in the indirect pair is capable of
connection to the first test channel receiver 111 and
the second measurement port in the indirect pair is
capable of connection to the second test channel
receiver 112.   In the illustrated example, there are
two direct pairs: first direct pair comprising
measurement ports 103_1 and 103_3 and second direct pair
comprising measurement ports 103_2 and 103_4.   Also in
the specific example, there are two indirect pairs:
first indirect pair comprising measurement ports 103_1
and 103_4 and second indirect pair comprising
measurement ports 103_2 and 103_3. Measurement ports 103
capable of connection to the same test channel
receiver, either the first test channel receiver 111 or
the second test channel receiver 112, are herein
referred to as "proximal pairs".   An N-port DUT has
$N(N-2)/4$ unique proximal pairs of measurement ports
103.   In the specific illustrated embodiment having
four measurement ports, the proximal pairs are
measurement ports 103_1 and 103_2, measurement ports 103_3
and 103_4.

[17]   In the TRL calibration process and with specific
reference to FIGURE 2 of the drawings, a high reflect
calibration standard 301 ("the reflect 301") is
measured at all measurement ports 103.   The reflect 301
may be either a short or an open circuit with or
without an offset.   In one embodiment of the process,
it is not necessary to know the type of reflect
standard used, but it is important to know the phase

11

offset of the reflect 301 in order to calculate an
electrical length of a thru calibration standard. In
an alternative embodiment, it is not necessary to know
the type of reflect or the phase offset of the reflect
calibration standard as long as the electrical length
of the thru calibration standard is known. In the
illustrated example, the reflect 301 is connected to
measurement port 103_1. The switching network 150 is
set so the measurement port 103_1 is connected to the
first signal path 107 and the respective sampling arm
113_1 is connected to the first test channel receiver
111. All remaining unused measurement ports 103_2, 103_3
and 103_4 are terminated in their respective local
terminating loads 104 and their respective sampling
arms 113 are connected to the sampling arm terminating
loads 116_2, 116_3, and 116_4. As one of ordinary skill in
the art appreciates, for measurement of the measurement
port 103_1 only the switch network configuration that
terminates in a characteristic impedance for those
measurement ports 103 that are capable of connection to
the first test channel receiver 111 are important to
the results. Because the isolation of the switches
that comprise the switch network 150 is so high, the
measurement ports 103 capable of connection to the
second test channel receiver 112 do not figure in the
high reflect measurement that uses the first test
channel receiver 111. Similarly, the measurement ports
103 capable of connection to the first test channel
receiver 111 do not figure in the high reflect

12

measurement that uses the second test channel receiver 112. The signal generator 105 is then swept through a desired frequency range as programmed by an operator and measurements are taken at specific frequencies across the range. During the frequency sweep the VNA 200 measures a reference signal as well as a reflected signal and stores a ratio of the measured reflected signal level at the test channel receiver, 111 in the example, over the measured signal level at the reference receiver, 201 in the example. The system stores a resulting ratio, which is a frequency dependant reflection coefficient, herein referred to as a high reflect characteristic for measurement port 103_1.

$A_{reflect\_1}/R1_{reflect\_1}$

[18]   The same process of measuring the reflect 301 is repeated for each measurement port 103. For each measurement port, the switch network 150 is configured so that the measurement port 103 with the reflect 301 receives the stimulus signal 105 and the switch network 150 has a sampling arm 113 arrangement whereby the reflected signal is measured by the appropriate test port 111 or 112. The unused measurement ports 103 are terminated in the local characteristic impedance 104 in the switching network 150. The sampling arms 113 of the unused measurement ports 103 are also terminated in the respective sampling arm terminating loads 116. The signal generator 105 stimulates the appropriate signal path 107 or 108 with a signal that is swept over the

13

same desired frequency range as in the reflection measurement of measurement port 103_1. The VNA 200 measures and stores a measurement of a ratio of the measured stimulus signal level over measured reflection signal yielding a frequency dependent array of reflected signal level over the stimulus signal, either $A_{reflect\_n}/R1_{reflect\_n}$ or $B_{reflect\_n}/R2_{reflect\_n}$, where "n" refers to the measurement port 103.

[19] With specific reference to FIGURE 3 of the drawings, a next step in the calibration process connects and measures a low-loss delay line calibration standard 401 ("the line 401") between each direct pair and indirect pair of measurement ports 103. The line 401 may be an airline i.e. a delay line having an air dielectric, which is commonly used in metrology laboratories. Alternatively and as typical for on-wafer measurements, a delay line may be used. The delay of the line 401 is unknown, but the physical dimensions of the line 401 relate to a valid range of calibration frequencies. Additional delay line calibration standards can be used to cover a broader frequency range as desired. The delay of the line 401 is defined over a range of frequencies bounded by approximately more than 20 degrees phase shift at a lowest specified frequency and less than 160 degrees phase shift at a highest specified frequency. At frequencies around 500 MHz and below, coaxial airline dimensions become very large and not practical. To measure at the lower frequencies, and with specific

14

reference to FIGURE 5 of the drawings, two high-quality matched loads 501 ("the matched loads 501") are connected to each measurement port 103 of the direct or indirect pair being measured. The matched loads 501 are used for calibrating the VNA 200 in a frequency range down to the lowest VNA frequency. The resulting calibration values of the line 401 and the matched loads 501 are different, but the algorithmic formulations using the measured ratios are the same.

[20] With specific reference to FIGURE 3 of the drawings in which the line 401 is measured between the first direct pair comprising measurement ports 103_1 and 103_3, the transfer switch 106 is set so that the signal generator 105 stimulates the first signal path 107 and the second signal path 108 is terminated at the source 109. The switch network 150 is configured so that the measurement port 103_1 accepts the stimulus signal from the first signal path 107 and the signal from the sampling arm 113_1 is presented to the first test port 111. The switch network 150 is further configured so that the measurement port 103_3 is terminated in the transfer switch characteristic impedance 109 through second signal path 108 and a transmitted signal is presented to the second test port 112 through sampling arm 113_3. The signal generator 105 sweeps the desired frequency range and the VNA 200 measures signal level from the first and second test channel receivers 111, 112 and the first and second reference receivers 201, 202 and stores the results in data arrays. For

15

purposes of clarity and consistency only, when the
signal generator 105 is connected to the first signal
path 107, all resulting measurements are considered
forward direction measurements. Accordingly, the
measurements made of the line 401 in the forward
direction are represented as the data arrays:

$A_{f\_line\_13}$,
$B_{f\_line\_13}$,
$R1_{f\_line\_13}$, and
$R2_{f\_line\_13}$.

where each array comprises a series of measured points
at specific frequencies along the desired frequency
range.

[21]   With specific reference to FIGURE 4 of the
drawings, the line 401 remains connected and the
transfer switch 106 is reconfigured so that the signal
generator 105 stimulates the second signal path 108 and
the first signal path 107 is terminated in the transfer
switch characteristic impedance 109 at the source. The
configuration of the switch network 150 is not changed
from the forward direction measurements. The signal
generator 105 again sweeps the desired frequency range
and the VNA 200 measures signal level from the first
and second test channel receivers 111, 112 and the
first and second reference receivers 201, 202 and
stores them in data arrays. For purposes of clarity and
consistency only, when the signal generator 105 is
connected to the second signal path 108, all resulting

16

measurements are considered reverse direction measurements. Accordingly, the measurements made of the line 401 in the reverse direction are represented as the data arrays:

$A_{r\_line\_13}$,

$B_{r\_line\_13}$,

$R1_{r\_line\_13}$, and

$R2_{r\_line\_13}$.

where each array comprises a series of measured points at specific frequencies along the desired frequency range.

[22]   If a broader frequency range is necessary, the same measurement procedure is performed on the first direct pair, measurement ports 103_1 and 103_3 in the specific embodiment, with a different airline covering a different frequency band. In addition, the matched loads 501 as shown in FIGURE 5 of the drawings may be used to simulate a high loss line having a perfect match in order to take measurements at lower frequencies than are practical with an airline calibration standard. Depending upon the matched load, the quality of the match at higher frequencies, and the desired frequency range, the matched loads may be used in place of the airline calibration standard. As new measurements are made for the different frequency ranges using the appropriate calibration standards, the results are stored in the forward and reverse direction arrays with each data point corresponding to a specific

17

stimulus signal frequency. Accordingly, the
calibration frequency band can extend over more
frequencies than is possible with a single airline
calibration standard.

[23]   With specific reference to FIGURE 6 of the
drawings, a next step in the calibration process is to
connect and measure a source terminated through
calibration standard 601 ("the thru 601") between each
direct pair and if there are more than two measurement
ports 103, each indirect pair. The thru 601 may have
either a zero length or a non-zero length and in one
embodiment, it is not necessary that the electrical
length be a known value. In an alternate embodiment,
if the electrical length of the thru 601 is known, it
is not necessary to know the phase offset of the high
reflect calibration standard 301. For on-wafer
measurements, it is not possible to obtain a high
quality zero thru calibration standard. Accordingly,
for on-wafer measurements, a non-zero thru calibration
standard and zero offset high reflect calibration
standard is typically used.

[24]   The first measurement of the thru 601 is made of a
source terminated thru 601. Using the first direct
pair as an example, the transfer switch 106 is set so
that the signal generator 105 stimulates the first
signal path 107 and the second signal path 108 is
terminated in the transfer switch characteristic
impedance 109. The switch network 150 is configured so
that the measurement port 103_1 accepts the stimulus

18

signal from the first signal path 107 and the sampling arm 113_1 is connected to the first test port 111. The switch network 150 is further configured so that the measurement port 103_3 is terminated in the transfer switch characteristic impedance 109 through second signal path 108 and the sampling arm 113_3 is connected to the second test port 112. The unused measurement ports 103 are terminated in the local characteristic impedances 104 and the unused sampling arms 113 are terminated in local sampling arm terminating loads 116. The signal generator 105 sweeps the desired frequency range and the VNA 200 measures the signal level from the first and second test channel receivers 111, 112 and the first and second reference receivers 201, 202 and stores the results in memory. According to the nomenclature used for purposes of the present disclosure, because the signal generator 105 is connected to the first signal path 107, the resulting measurements are considered forward direction measurements. Accordingly, the measurements made of the source terminated thru 601 in the forward direction are represented as the arrays:

A_{fnm_thru},

B_{fnm_thru},

$R1_{fnm\_thru}$, and

$R2_{fnm\_thru}$.

where each array comprises a series of measured points at specific frequencies along the desired frequency

19

range and subscripts "n" and "m" refer to the measurement ports between which the thru 601 is connected where "m" is the source port and "n" is the receive port.

[25]   With specific reference to FIGURE 7 of the drawings, the thru 601 remains connected and the transfer switch 106 is set for the reverse measurements. Specifically, the signal generator 105 stimulates the second signal path 108 and the first signal path is terminated in the transfer switch characteristic impedance 109. The switch network 150 is unchanged. The signal generator 105 again sweeps the desired frequency range and the VNA 200 measures a signal level from the first and second test channel receivers 111, 112 and the first and second reference receivers 201, 202 and stores them in memory. Because the signal generator 105 is connected to the second signal path 108, the resulting measurements are considered reverse direction measurements. Accordingly, the measurements made of the source terminated thru 601 in the reverse direction are represented as the arrays:

A_{rnm_thru},
B_{rnm_thru},
$R1_{rnm\_thru}$, and
$R2_{rnm\_thru}$.

where each array comprises a series of measured points at specific frequencies along the desired frequency

20

range.

[26]   At this point in the process, enough measurements
have been taken to calculate forward and reverse
directivity, source match and reflection tracking for
all direct and indirect pairs. The present
organization of the process, however, completes all
measurements and then calculates all ten error terms
for each direct, indirect, and proximal pairs of
measurement ports. It is further possible with the
measurements taken thus far to calculate an electrical
length of the sum of the thru calibration standard 601
and zero or offset high reflect standard 301 that is
used in the calibration process by extrapolating an
argument of the reflection tracking term to DC. It is
also possible to determine a type of high reflect
standard used in the calibration process. Additional
details of the specific error term and electrical
length calculations are described herein.

[27]   With specific reference to FIGURE 8 of the
drawings and with the thru 601 still connected, the
transfer switch 106 is configured so that the signal
generator 105 is in the first signal path 107 and the
second signal path 108 is terminated in the
characteristic impedance 109. The switch network 150
is configured so that the measurement port 103 is
connected to the first signal path 107 and the
respective sampling arm 113 is connected to the first
test channel receiver 111. The remaining unused
measurement ports 103 capable of connection to the

21

first test channel receiver 111 are terminated at
respective local characteristic impedances 104. In
addition, the sampling arms 113 of the unused
measurement ports 103 are terminated in local sampling
arm characteristic impedances 116. The switch network
150 is further configured so that the measurement port
103 capable of connection to the second test channel
receiver 112 in the first direct pair is terminated at
the respective local characteristic impedance 104 and
the respective sampling arm 113 is connected to the
second test channel receiver 112. The measurement
ports 103 of the direct pairs not being measured are
also terminated in local characteristic impedances and
the respective sampling arms 113 are terminated in
respective local sampling arm terminating loads 116.
The signal generator 105 is again swept through the
desired frequency range and for each frequency point in
the range, the VNA 200 measures a reflection response,
a transmission response and a stimulus of the locally
terminated thru 601 and stores the data in the
following arrays:

$A_{fnm\_termthru}$,

$B_{fnm\_termthru}$, and

$R1_{fnm\_termthru}$.

[28]   With specific reference to FIGURE 9 of the
drawings, and with the thru 601 still connected between
the measurement ports 103 of the first direct pair, the
transfer switch 106 is re-configured so that the signal

22

generator 105 is in the second signal path 108 and the first signal path 107 is terminated in the characteristic impedance 109. The switch network 150 is also reconfigured so that the measurement port 103 in the first direct pair that is capable of connection to the second test channel receiver 112, measurement port 103_3 in the illustrated example, is connected to the second signal path 108 and the respective sampling arm 113_3 is connected to the second test channel receiver 112. The measurement port 103 in the first direct pair that is capable of connection to the first test channel receiver 111, measurement port 103_1 in the illustrated example, is terminated in the respective local characteristic impedance 104_1 and the respective . sampling arm 113_1 is connected to the first test channel receiver 111. The measurement ports 103 of the direct pairs not being measured are locally terminated in their characteristic impedances 104. Additionally, the sampling arms 113 of the unused measurement ports 103 are terminated in their respective local sampling arm terminating loads 116. The signal generator 105 is swept through the desired frequency range and for each frequency point in the range, the VNA 200 measures a reflection response of the locally terminated thru 601, a transmission response of the locally terminated thru 601, and the level of the stimulus signal as measured at the second reference channel 202. The measured values are stored in data arrays:

$A_{rnm\_termthru}$,

23

$B_{rnm\_termthru}$, and

$R2_{rnm\_termthru}$.

[29]   The same process is followed to measure and record
similar measurements of the thru 601 for all remaining
direct pairs and indirect pairs of the measurement
ports 103. It is preferred to measure the same
frequency points for all calibration measurements along
the frequency range so that each array has a
corresponding measured value for each frequency point.
It is acceptable, however, to interpolate the data to
obtain a value for a specific frequency value as long
as the frequency value is within the boundary of the
lowest measured frequency and the highest measured
frequency in the desired frequency range and the
interval between measured frequencies is small enough
to fully characterize the DUT including any resonances
thereof. If multiple line calibration standards are
used to obtain a broader frequency range, the
measurements taken by the VNA 200 are stored in
appropriate array elements in a larger array having an
element for each frequency along the frequency range of
interest. Accordingly, multiple steps of connecting
calibration standards and making measurements may be
performed to completely populate a single data array.

[30]   With specific reference to Figure 10 of the
drawings, there is shown a flow graph between any first
port and any second port of the VNA 200. A multiport
embodiment has a similar calibration flow graph for
each of the direct pairs. The calibration flow graph

24

represents the forward directivity (shown as "EDF" in the '511 patent and Sx_{11} in the present teachings) 1901, forward source match (shown as "ESF" in the '511 patent and Sx_{22} in the present teachings) 1902, and forward reflection tracking error coefficients (shown as "ETF" in the '511 patent and $Sx_{12}Sx_{21}$ in the present teachings) 1903 for the X error adapter 1910. The calibration flow graph also represents reverse directivity (shown as "EDR" in the '511 patent and Sy_{11} in the present teachings) 1904, reverse source match (shown as "ESR" in the '511 patent and Sy_{22} in the present teachings) 1905, and reverse reflection tracking (shown as "ERR" in the '511 patent and $Sy_{12}Sy_{21}$ in the present teachings) error coefficients 1906 for the Y error adapter 1920. Not shown on the flow graph, but four remaining error coefficients that are also used in the ten term error correction process are forward transmission tracking (shown as "ETF" in the '511 patent and τ_{nm} in the present teachings where port "m" sources a stimulus and port "n" is the measurement port), forward load match (shown as "ELF" in the '511 patent and Γ_{m} in the present teachings for port "m"), reverse transmission tracking (shown as "ETR" in the '511 patent and τ_{mn} in the present teachings where port "n" sources a stimulus and port "m" is the measurement port), and reverse load match (shown as "ELR" in the '511 patent and Γ_{n} in the present teachings for port "n"). An embodiment of a method according to the present teachings determines the error coefficients for

25

each direct and indirect pair based upon measurements
of the TRL calibration standards for each direct and
indirect measurement port pair. The flow graph
represents an S-parameter matrix for the X error
adapter 1910, S_x, which corresponds to a subset of the
error artifacts for a first measurement port 103 in the
direct or indirect pair, and an S-parameter matrix for
the Y error adapter 1920, S_y, which corresponds to a
subset of the error artifacts for a second measurement
port 103 in the direct or indirect pair. The remaining
error coefficients are calculated from the X and Y
error adapter error artifacts.

[31]   S-parameter matrix S_{act} represents the S-parameters
of a calibration standard without the contribution of
the X and Y error adapters. The S-parameter matrix of
the X error adapter may be expressed as T-parameters
using the following known conversion where port 1
represents a port from which a measurement is taken and
port 2 represents a port that sources a stimulus
signal:

$$Tx = \begin{bmatrix} Tx_{11} & Tx_{12} \\ Tx_{21} & Tx_{22} \end{bmatrix} = \begin{bmatrix} \dfrac{1}{Sx_{21}} & \dfrac{-Sx_{22}}{Sx_{21}} \\ \dfrac{Sx_{11}}{Sx_{21}} & \dfrac{Sx_{12}Sx_{21}-Sx_{11}Sx_{22}}{Sx_{21}} \end{bmatrix} \qquad (1)$$

[32]   Accordingly, the matrix Sx may be converted into
corresponding T-parameters expressed as Tx. If the

26

matrix T_{act_thru} expresses the T-parameters of just the thru 601 and T_{meas_thru} expresses the T-parameters of the thru 601 as measured in context with the X and Y error adapters, then the following relationship holds true:

$$T_x T_{act\_thru} T_y = T_{meas\_thru} \qquad (2)$$

[33]   Similarly, if the matrix T_{act_line} expresses the T-parameters of just the line 401 and T_{meas_line} expresses the T-parameters of the line 401 as measured in context with the X and Y error adapters, then the following relationship holds true:

$$T_x T_{act\_line} T_y = T_{meas\_line} \qquad (3)$$

If the following relationships are defined:

$$T_{act\_x} = T_{act\_line} T_{act\_thru}^{-1} \qquad (4)$$

and

$$T_{meas\_x} = T_{meas\_line} T_{meas\_thru}^{-1} \qquad (5)$$

then the following equation can be written:

27

$$T_x T_{act\_x} = T_{meas\_x} T_x \qquad (6)$$

[34]   The thru 601 and the line 401 are each assumed to
be perfectly matched.   Therefore, the value of their
reflection coefficient in the respective actual S-
parameter matrix is set to zero. If the thru 601 has a
non-zero length transmission coefficient, it is defined
by $S_{21\_thru} = S_{12\_thru}$.   The line 401 has a transmission
coefficient defined by $S_{21\_line} = S_{12\_line}$.   From equation
(4), therefore T_{act_x} may be expressed as:

$$T_{act\_x} = \begin{bmatrix} \dfrac{S_{21\_thru}}{S_{21\_line}} & 0 \\ 0 & \dfrac{S_{21\_line}}{S_{21\_thru}} \end{bmatrix} \qquad (7)$$

[35]   Measurements of the source thru 601 and the source
terminated line 401, each provide eight frequency
dependent arrays of measured and stored results.
There are four thru forward reflection and transmission
arrays and four thru reverse reflection and
transmission arrays. The arrays of measured data for
the source terminated thru 601 are used in an
algorithmic formulation in the S-parameter domain to
compensate for the presence of the signal transfer
switch 106 prior to calculation of the T_{meas_x} matrix.

28

The effect of the transfer switch 106 of the uncorrected measured S-parameter for the thru and line calibration standards, S_{meas_line} and S_{meas_thru}, are corrected by the formulation given by:

$$S_{transferswitxh\_corrected} = \begin{bmatrix} \left(\dfrac{\dfrac{A_f}{R1_f} - \dfrac{A_r}{R2_r}\dfrac{R2_f}{R1_f}}{1 - \dfrac{R2_f}{R1_f}\dfrac{R1_r}{R2_r}} \right) & \left(\dfrac{\dfrac{A_r}{R2_r} - \dfrac{A_f}{R1_f}\dfrac{R1_r}{R2_r}}{1 - \dfrac{R2_f}{R1_f}\dfrac{R1_r}{R2_r}} \right) \\[2em] \left(\dfrac{\dfrac{B_f}{R1_f} - \dfrac{B_r}{R2_r}\dfrac{R2_f}{R1_f}}{1 - \dfrac{R2_f}{R1_f}\dfrac{R1_r}{R2_r}} \right) & \left(\dfrac{\dfrac{B_r}{R2_r} - \dfrac{B_f}{R1_f}\dfrac{R1_r}{R2_r}}{1 - \dfrac{R2_f}{R1_f}\dfrac{R1_r}{R2_r}} \right) \end{bmatrix} \qquad (8)$$

where A_f, B_f, $R1_f$ and $R2_f$ are the forward direction raw measurement data, i.e. when the signal transfer switch 106 is directing the signal generator 105 to the first signal path 107, and A_r, B_r, $R1_r$ and $R2_r$ are the reverse direction raw measurement data, i.e. when the signal transfer switch 106 is directing the signal generator 105 to second signal path 108. After using this correction, the relevant S-parameter matrices are $S_{measnm\_thru\_transferswitch\_corrected}$ and $S_{measnm\_line\_transferswitch\_corrected}$ where "n" and "m" represent the port numbers between which the respective calibration standards are measured.

[36]   Using the first direct pair as an example, measurement ports 103_1 and 103_3, a corrected S-

parameter matrix of the thru 601 measured in cascaded combination with the X and Y error adapters for the first direct pair is expressed herein as $S_{meas13\_thru\_transferswitch\_corrected}$. The correction formulation shown in equation (8) uses the arrays: A_{f13_thru}, B_{f13_thru}, $R1_{f13\_thru}$, $R2_{f13\_thru}$, A_{r13_thru}, B_{r13_thru}, $R1_{r13\_thru}$, and $R2_{r13\_thru}$ to calculate $S_{meas13\_thru\_transferswitch\_corrected}$. Converting the $S_{meas13\_thru\_tranferswitch\_corrected}$ matrix to the corresponding T-parameters using equation (1) yields matrix $T_{meas13\_thru\_transferswitch\_corrected}$. To obtain the $S_{meas13\_line\_transferswitch\_corrected}$ matrix for the first direct pair, the correction formulation shown in equation (8) uses the arrays: A_{f13_line}, B_{f13_line}, $R1_{f13\_line}$, $R2_{f13\_line}$, A_{r13_line}, B_{r13_line}, $R1_{r13\_line}$, and $R2_{r13\_line}$. Converting the corrected $S_{meas13\_line\_transferswitch\ corrected}$ matrix to the corresponding T-parameters, yields matrix $T_{meas13\_line\_transferswitch\_corrected}$. The $T_{meas13\_thru\_transferswitch\_corrected}$ and $T_{meas13\_line\_transferswitch\_corrected}$ matrices are used in equations (4) and (5) to calculate T_{act_x} and T_{meas_x}.

[37]   Referring now to the general case, T_x is the T-parameter matrix for the X error adapter and is defined by its matrix elements as:

$$Tx = \begin{bmatrix} Tx_{11} & Tx_{12} \\ Tx_{21} & Tx_{22} \end{bmatrix} \qquad\qquad (9)$$

T_{meas_x} is also defined by its matrix elements, and is

30

represented as:

$$T_{meas\_x} = \begin{bmatrix} T_{meas\_x11} & T_{meas\_x12} \\ T_{meas\_x21} & T_{meas\_x22} \end{bmatrix} \tag{10}$$

From equation (5), T_meas_x for measurement ports 103_1 and 103_3, which is expressed as T_meas13_x, is calculated using the T_meas13_thru_transferswitch_corrected and T_meas13_line_transferswitch_corrected matrices. Accordingly:

$$T_{meas13\_x} = T_{meas13\_line\_transferswitch\_corrected} T_{meas13\_thru\_transferswitch\_corrected}^{-1}$$

[38] Using the relationship in equations (4), substituting the terms in equation (6), and eliminating the S_{21_thru}/S_{21_line} term, the following general equation can be written:

$$\frac{Tx_{21}}{Tx_{11}} = \frac{(-T_{meas\_x11} + \sqrt{4T_{meas\_x12}T_{meas\_x21} + (T_{meas\_x11} - T_{meas\_x22})^2} + T_{meas\_x22})}{2T_{meas\_x12}} \tag{11}$$

and

$$\frac{Tx_{22}}{Tx_{12}} = \frac{(-T_{meas\_x11} + \sqrt{4T_{meas\_x12}T_{meas\_x21} + (T_{meas\_x11} - T_{meas\_x22})^2} + T_{meas\_x22})}{2T_{meas\_x12}} \tag{12}$$

31

Based upon the T-parameter to S-parameter conversion, $\frac{Tx_{21}}{Tx_{11}}$ and $\frac{Tx_{22}}{Tx_{12}}$ in terms of the corresponding S-parameter error adapter matrix may also be expressed as:

$$\frac{Tx_{21}}{Tx_{11}} = Sx_{11} = B \tag{13}$$

and

$$\frac{Tx_{22}}{Tx_{12}} = Sx_{11} - \frac{Sx_{12}Sx_{21}}{Sx_{22}} = A \tag{14}$$

[39]   As one of ordinary skill in the art can appreciate, equations (11) and (12) are equal. Because there is a square root in the solution, there are two possible mathematical solutions. The smaller valued solution, defined by B, corresponds to the directivity error coefficient, S_{x11} 1901, of error adapter X. The larger valued solution, defined by A, is a mathematical combination of source match 1902 and reflection tracking 1903.

[40]   As mentioned before, at frequencies around 500 MHz and below, the dimensions of the line 401 become very

32

large and not practical. Calculation of the directivity
1901 and the solution represented by A for the lower
frequencies uses the measurements taken of the two
high-quality matched loads 501 instead of the line 601.
It is assumed that the matched loads 501 are perfectly
matched to the measurement port and have a zero
reflection coefficient. The same algorithmic
formulations shown in equations (5) through (14) are
used. To understand the usage of the measurement
results from the two matched loads, note that the thru
601 has a non-zero-length transmission coefficient
defined by $S_{12thru}=S_{12thru}$. The matched loads 501 have a
transmission isolation coefficient defined by
$S_{21load}=S_{12load}$. Due to the high isolation between the
matched loads 501, S_{21load} is close to a zero value.
Accordingly, S_{21load} is set to a very small, non-zero
value, such as 10^{-10} in order to avoid division by zero
ambiguity in the S-parameter to T-parameter conversion.
From this, T_{act_x} at the lower frequencies can be
calculated and is given by:

$$T_{act\_x}=\begin{bmatrix} \dfrac{S_{21\_thru}}{10^{-10}} & 0 \\ 0 & \dfrac{10^{-10}}{S_{21\_thru}} \end{bmatrix} \tag{15}$$

[41]   As shown before, by using equations (4) and (5),
substituting results into equation (6) and eliminating
the $S_{21\_thru}/10^{-10}$ term, equations (11) and (12) are

33

derived. The S-parameters from the matched loads 501 are corrected using equation (8) to yield $S_{meas13\_load\_transferswitch\_corrected}$, which is then converted using equation (1) to yield $T_{meas13\_load\_transferswitch\_corrected}$. The $T_{meas13\_load\_transferswitch\_corrected}$ term is used to calculate T_{meas13_x} in place of the terms measuring the line 401. The calculations in equations (11) and (12), therefore, are the same as for the line 401.

[42] A similar process is performed to calculate terms in the error adapter Y. Beginning with equations (2) and (3) and defining the following relationships:

$$T_{act\_y} = T_{act\_thru}{}^{-1} T_{act\_line} \qquad (16)$$

and

$$T_{meas\_y} = T_{meas\_thru}{}^{-1} T_{meas\_line} \qquad (17)$$

then the following equation can be written:

$$T_{act\_y} T_y = T_y T_{meas\_y} \qquad (18)$$

[43] With specific reference to Figure 10 of the drawings, the known conversion for T-parameter matrix for the error adapter Y in terms of the S-parameters where port 1 is on the right and port 2 is on the left

34

when looking at the DUT 101 is:

$$Ty = \begin{bmatrix} Ty_{11} & Tx_{12} \\ Ty_{21} & Ty_{22} \end{bmatrix} = \begin{bmatrix} \dfrac{1}{Sy_{12}} & \dfrac{-Sy_{11}}{Sy_{12}} \\ \dfrac{Sy_{22}}{Sy_{12}} & \dfrac{Sy_{12}Sy_{21} - Sy_{11}Sy_{22}}{Sy_{12}} \end{bmatrix} \tag{19}$$

[44]   Accordingly, the matrix Sy may be converted into corresponding T-parameters expressed as Ty. The $T_{meas13\_thru\_corrected}$ and $T_{meas13\_line\_corrected}$ matrices have already been calculated and are used in equation (17) to calculate T_{meas13_y}, where:

$$T_{meas13\_y} = \begin{bmatrix} T_{meas13\_y11} & T_{meas13\_y12} \\ T_{meas13\_y21} & T_{meas13\_y22} \end{bmatrix} \tag{20}$$

[45]   Using equation (18), substituting the relationships in equations (16) and (17) and eliminating the S_{21thru}/S_{21line} term, the following equation for the first direct pair can be written:

$$\frac{Ty_{12}}{Ty_{11}} = \frac{\left(-T_{meas13\_y11} + \sqrt{4T_{meas13\_y12}T_{meas13\_y21} + (T_{meas13\_y11} - T_{meas13\_y22})^2} + T_{meas13\_y22}\right)}{2T_{meas13\_y21}} \tag{21}$$

and

$$\frac{Ty_{22}}{Ty_{21}} = \frac{(-T_{meas13\_y11} + \sqrt{4T_{meas13\_y12}T_{meas13\_y21} + (T_{meas13\_y11} - T_{meas13\_y22})^2} + T_{meas13\_y22})}{2T_{meas13\_y21}} \quad (22)$$

[46]   From equation (19), $\dfrac{Ty_{12}}{Ty_{11}}$ and $\dfrac{Ty_{22}}{Ty_{21}}$ in terms of the corresponding the S-parameters for the error adapter Y is also given by:

$$\frac{Ty_{12}}{Ty_{11}} = -Sy_{11} = D \quad\quad\quad (23)$$

and

$$\frac{Ty_{22}}{Ty_{21}} = \frac{Sy_{12}Sy_{21}}{Sy_{22}} - Sy_{11} = C \quad\quad\quad (24)$$

[47]   As one of ordinary skill in the art can appreciate, equations (21) and (22) are equal and because of the square root have two solutions. The smaller value or the first solution, defined by Sy_{11}, corresponds to the directivity error of the Y error adapter. The larger value or the second solution, defined by C, corresponds to the error coefficient, $\dfrac{Sy_{12}Sy_{21}}{Sy_{22}} - Sy_{11}$, for the Y error adapter.

[48]   With reference to the portion of the calibration
procedure that measures the high reflect calibration
standard as illustrated in FIGURE 2 of the drawings,
the high reflect standard 301, is connected to one
measurement port 103_1 of the first direct pair and the
same high reflect standard 301 is disconnected from the
measurement port 103_1 and is then connected to the
other measurement port 103_3 of the first direct pair.
With specific reference to FIGURE 10 of the drawings
the following equation can be written:

$$\Gamma_{meas\_reflect\_x} = Sx_{11} + \frac{Sx_{12}Sx_{21}\Gamma_{act\_reflect\_x}}{1 - Sx_{22}\Gamma_{act\_reflect\_x}} \tag{25}$$

where $\Gamma_{meas\_reflect\_x}$ is the measured reflection
coefficient of the high reflect standard 301 at the
measurement port capable of connection to the first
test channel receiver, measurement port 103_1 in the
first direct pair, and $\Gamma_{act\_reflect\_x}$ is the actual
reflection coefficient of the high reflect standard at
the same measurement port 103_1. The same high reflect
calibration standard 301 is connected to the opposite
port in the first direct pair, measurement port 103_3 in
the specific example. With respect to the error
adapter Y, the following equation can also be written:

37

$$\Gamma_{meas\_reflect\_y} = Sy_{11} + \frac{Sy_{12}Sy_{21}\Gamma_{act\_reflect\_y}}{1 - Sy_{22}\Gamma_{act\_reflect\_y}} \tag{26}$$

where $\Gamma_{meas\_reflect\_y}$ is the measured reflection coefficient of the high reflect standard 301 at measurement port 103_3 and $\Gamma_{act\_reflect\_y}$ is the actual reflection coefficient of the high reflect standard at the measurement port 103_3. A value for the measured reflection coefficient of the high reflect standard, $\Gamma_{meas\_reflect\_x}$, for the measurement port 103_1 may be obtained from the following measured and stored arrays $A_{reflect\_1}/R1_{reflect\_1}$. Similarly, a value for the measured reflection coefficient of the high reflect standard, $\Gamma_{meas\_reflect\_y}$, for the measurement port 103_3 may be obtained from the following measured and stored arrays $B_{reflect\_3}/R2_{reflect\_3}$. Because the same high reflect standard is connected to measurement ports 103_1 and 103_3, it is possible to solve for $\Gamma_{act\_reflect\_x}$ in equation (25) and $\Gamma_{act\_reflect\_y}$ in equation (26), and set the Γ terms equal to each other. From the resulting relationship and equations (13), (14), (23), (24), (25) and (26), the following relationship can be written:

$$Sx_{22} = \frac{(B - \Gamma_{meas\_reflect\_x})(C - \Gamma_{meas\_reflect\_y})Sy_{22}}{(A - \Gamma_{meas\_refkect\_x})(D - \Gamma_{meas\_reflect\_y})} \tag{27}$$

As one of ordinary skill in the art appreciates,

equation (27) has two unknown terms, but permits the expression of Sx_{22} in terms of Sy_{22}. Accordingly, another relationship is necessary in order to solve for these two unknown terms.

[49]   With specific reference to FIGURES 7 and 10, the following equation can also be written:

$$\Gamma_{meas\_thru11} = Sx_{11} + \frac{Sx_{12}Sx_{21}Sy_{22}}{1 - Sx_{22}Sy_{22}} \tag{28}$$

where Γ_{meas_thru11} is measured as $A_{fl3\_thru}/R1_{fl3\_thru}$ for the measurement port of the first direct pair that is capable of connection to the first test channel receiver 111. From (13), (14), (23) and (24), the following can be written:

$$Sx_{22} = \sqrt{\frac{(B - \Gamma_{meas\_reflect\_x})(C - \Gamma_{meas\_reflect\_y})(B - \Gamma_{meas\_thru11})}{(A - \Gamma_{meas\_reflect\_x})(D - \Gamma_{meas\_reflect\_y})(A - \Gamma_{meas\_thru11})}} \tag{29}$$

Sx_{22} is the source match error coefficient at the first measurement port 103. Due to the square root function in equation (29), there are 2 possible solutions for Sx_{22}. Additional information is needed, therefore, to solve for the appropriate solution for the present measurement.

[50]   The reflection-tracking error coefficient $S_{x12}S_{x21}$

is calculated for each of the two possible solutions to yield:

$$S_{X12}S_{X21} = (B - A) S_{X22\_solution\_1} \qquad (30)$$

and

$$S_{X12}S_{X21} = (B - A) S_{X22\_solution\_2} \qquad (31)$$

[51]   Squaring either equation (30) or (31) provides the complex value $(S_{x12}S_{x21})^2$. Because the square of the reflection-tracking coefficient is a complex variable, its square root has two solutions. Each of the two solutions has the same magnitude, but they are 180 degrees out of phase. Only one of the solutions is proper. To select the proper solution, both solutions for reflection tracking are solved at DC. Based upon the properties of reflection tracking, the argument of the proper solution is zero at DC. Given this boundary condition, therefore, the solution for reflection tracking with an argument closest to zero at a DC frequency is the proper solution and a value for the reflection tracking parameter may be determined.

[52]   Because S-parameter measurements are not taken at DC, the function that is fit to the argument of the reflection-tracking coefficient is extrapolated to a

40

frequency value at DC. Specifically, the argument, θ, for each solution is calculated as a function of frequency. A first solution for the argument is represented as θ(f)$_{sx22\_solution1}$ and a second solution is represented as θ(f)$_{sx22\_solution2}$. For each solution, as the calculated function of frequency crosses through +180 or -180 degree points, 360 degrees is added to form a continuous function of phase as a function of frequency. Each resulting continuous function is fitted using a least sum squared fitting algorithm with a two term polynomial where f represents a frequency value and where:

$$\theta(f)_{sx22\_solution1} = \sum_{i=0}^{1} A_i f^i = A_{0\_sx22\_solution1} + A_{1\_sx22\_solution1} f \qquad (32)$$

and

$$\theta(f)_{sx22\_solution2} = \sum_{i=0}^{1} A_i f^i = A_{0\_sx22\_solution2} + A_{1\_sx22\_solution2} f \qquad (33)$$

[53] Each two term polynomial defines a straight line with slope, A_{1_sx22}, and y-intercept, A_{0_sx22}. The y-intercept represents a value of θ at DC. Of the two possible solutions for A_{0_sx22}, only one of the solutions has a y-intercept of zero. Accordingly, whichever value, $A_{0\_sx22\_solution1}$ or $A_{0\_sx22\_solution2}$, is closest to a zero value is the proper solution. When the proper solution is identified, both the magnitude and phase are then calculated for the reflection tracking

41

coefficient, $S_{x12}S_{x21}$. From the calculation of the
reflection tracking coefficient, source match error,
S_{x22}, is calculated where:

$$S_{X22} = \frac{S_{x12}S_{x21}}{B - A} \qquad (34)$$

The factors represented as "B" and "A" are known from
equations (13) and (14). Accordingly, the source match
error, S_{x22}, is also fully determinable.

[54]   When a value for Sx_{22} is known, a value for Sy_{22} may
be calculated from equation (27). Sy_{22} is the source
match error coefficient of error adapter Y at the
measurement port capable of connection to the second
test channel receiver 112, which is measurement port
103_3 in the specific example.

[55]   A definite value for Sy_{22} and equations (23), (24)
and (27) permit calculation of a reflection tracking
for the error adapter Y and is given by:

$$Sy_{12}Sy_{21} = (D - C)Sy_{22} \qquad (35)$$

[56]   Accordingly, the directivity, source match and
reflection tracking for the error adapter X and the
error adapter Y for the first direct pair is
determined. The same process is followed to calculate

42

the directivity, source match, and reflection tracking
for the X and Y error adapters for each direct and
indirect pair. The X error adapters are defined as the
error artifacts presented in series with the
measurement ports 103 capable of connection to the
first test channel receiver 111. Similarly, the Y
error adapters are defined as the error artifacts
presented in series with the measurement ports 103
capable of connection to the second test channel
receiver 112.

[57]   In the specific four-port embodiment, the
measurements and calculations described herein for
measurement ports 103_1 and 103_3 yield directivity,
source match and reflection tracking for the error
adapter X related to measurement port 103_1 and
directivity, source match, and reflection tracking for
the error adapter Y related to measurement port 103_3.
The same measurements and calculations described herein
for measurement ports 103_1 and 103_3 are performed for
the second direct pair and if source terminated
measurements are taken for the indirect pairs, all
indirect pairs as well. If source terminated
measurements are not taken for the indirect pairs,
directivity, source match, and reflection tracking are
determined according to the teachings US patent
application Ser. No. 09/954,962 (herein "the '962
patent application"), the teachings of which are hereby
incorporated by reference. In a certain multiport
embodiment, the same measurements and calculations are

43

made for each direct pair and indirect pair to yield directivity, source match and reflection tracking for the error adapter X related to the measurement port of the direct or indirect pair capable of connection to the first test channel receiver 111 and directivity, source match, and reflection tracking for the error adapter Y related to the measurement port of the direct or indirect pair capable of connection to the second test channel receiver 112. Accordingly, an N port DUT 100 has $N(N-1)/2$ different X and Y error adapters associated therewith. In another multiport embodiment, the disclosed measurements are made for all direct pairs to calculate directivity, source match, and reflection tracking and the error terms for the indirect pairs are calculated according to the '962 Patent Application.

[58]   Using the forward reflection and transmission measurements made on the locally terminated thru 601, which in a specific example of the first direct pair are the $A_{f13\_termthru}$, $B_{f13\_termthru}$, and $R1_{f13\_termthru}$ arrays, it is possible to solve for a load match error coefficient presented at the measurement port capable of connection to the second test channel receiver 112 and a forward transmission tracking error coefficient for the first direct pair. The load match for the measurement port 103_3, Γ_{L3}, and forward transmission tracking for the first direct pair, τ_{13}, are given by:

$$\Gamma_{L3} = \frac{Sx_{11} - (A_{f13\_termthru} / R1_{f13\_termthru})}{Sx_{11}Sx_{22} - Sx_{12}Sx_{21} - Sx_{22}(A_{f13\_termthru} / R1_{f13\_termthru})} \qquad (36)$$

and

$$\tau_{13} = (B_{f13\_termthru} / R1_{f13\_termthru})(1 - Sx_{22}\Gamma_{L3}) \qquad (37)$$

[59]   Using the reverse reflection and transmission measurements made on the locally terminated thru 601, which in a specific example of the first direct pair are the $A_{r13\_termthru}$, $B_{r13\_termthru}$, and $R2_{f13\_termthru}$ arrays, it is possible to solve for a load match error coefficient presented at the measurement port capable of connection to the first test channel receiver 111 and a reverse transmission tracking error coefficient for the first direct pair. The load match for the measurement port 103_1, Γ_{L1}, and the reverse transmission tracking coefficient, τ_{31}, are given by:

$$\Gamma_{L1} = \frac{Sy_{11} - (B_{r13\_termthru} / R2_{r13\_termthru})}{Sy_{11}Sy_{22} - Sy_{12}Sy_{21} - Sy_{22}(B_{r13\_termthru} / R2_{r13\_termthru})} \qquad (38)$$

and

$$\tau_{31} = (A_{r13\_termthru} / R2_{r13\_termthru})(1 - Sy_{22}\Gamma_{L1}) \qquad (39)$$

45

[60]   In the specific illustrated embodiment, using the
measurements made of the locally terminated thru 601
for the second direct pair, the same algorithmic
formulations shown in equations (36) through (39) as
described for the first direct pair are applied to the
measurement ports of the second direct pair.
Accordingly, forward and reverse directivity, source
match, reflection tracking and load match error
coefficients for each measurement port in the direct
and indirect pairs and forward and reverse transmission
tracking error coefficients for all direct and indirect
pairs are determined.

[61]   In a multiport embodiment of a method according to
the teachings of the present invention, the forward and
reverse directivity, forward and reverse source match,
forward and reverse reflection tracking, forward and
reverse load match, and forward and reverse
transmission tracking error coefficients for each
measurement port in all of the direct pairs are
similarly determined.

[62]   Because the directivity, source match and
reflection tracking are fully determinable,
characteristics of the high reflect calibration
standard 301 may also be calculated. Using equations
(25) or (26) and solving for $\Gamma_{act\_reflect\_x}$ or $\Gamma_{act\_reflect\_y}$,
yields:

46

$$\Gamma_{act\_reflect\_x} = \frac{B - \Gamma_{meas\_reflect\_x}}{\left(A - \Gamma_{meas\_reflect\_x}\right) S_{x22}} \qquad (40)$$

or

$$\Gamma_{act\_reflect\_y} = \frac{D - \Gamma_{meas\_reflect\_y}}{\left(C - \Gamma_{meas\_reflect\_y}\right) S_{y22}}$$

[63]   The argument of $\Gamma_{act\_reflect\_x}$ as a function of
frequency, where 360 degrees is added as the function
passes through the +/-180 degree points as previously
described, is fitted to a least sum squared fitting
algorithm with a two term polynomial as in equations
(32) or (33). The resulting two term polynomial that
describes the proper function includes $A_{0\_\Gamma act\_reflect\_x}$ as
the y-intercept and $A_{1\_\Gamma act\_reflect\_x}$ as the slope. If
$A_{0\_\Gamma act\_reflect\_x}$ has a value closest to 180 degrees, then
the high reflect calibration standard 301 has a short
circuit reflection coefficient. If $A_{0\_\Gamma act\_reflect\_x}$ has a
value closest to 0 degrees, then the high reflect
calibration standard 301 has an open circuit reflection
coefficient. Accordingly, the type of high reflect
calibration standard measured can be deduced from the
least sum square fit calculations. If the electrical
length of the thru 601 is unknown, however, it is
necessary to know a phase offset of the high reflect
calibration standard 301 for additional correction. If

the electrical length of the thru is known, it is possible to determine a type of high reflect 301 and calculate the phase offset of the reflect 301.

[64]   The forward and reverse transmission tracking error coefficients of the proximal pairs are: τ_{12}, τ_{21}, τ_{34}, and τ_{43}, which may be determined either through measurement and calculation or through pure calculation. The method for pure calculation of the forward and reverse transmission tracking error coefficients is taught in US Patent Application Ser. No. 10/098,040, the teachings of which are hereby incorporated by reference.

[65]   Alternatively and with specific reference to FIGURE 11 of the drawings, the forward transmission tracking error coefficient for each proximal pair where both measurement ports 103 of the proximal pair are capable of connection to the first test channel receiver 111 is measured and calculated by connecting the thru 601 between the measurement ports 103 of the proximal pair, connecting the signal generator 105 to a first one of the measurement ports 103 of the proximal pair and terminating the sampling arm 113 in a local terminating impedance 116. For purposes of nomenclature, the first measurement port 103 of the proximal pair is designated as "port F". The other measurement port 103 of the proximal pair, which for purposes of nomenclature is designated as "port G", is terminated in a local terminating impedance 104, and

48

the respective sampling arm 113 is connected to the first test channel receiver 111. The VNA 200 measures and stores a ratio of a transmission response over the reference signal, $A_{fFG\_termthru}/R1_{fFG\_termthru}$. The ratio is used in the transmission tracking error coefficient equation where:

$$\tau_{FG} = (A_{fFG\_termthru} / R1_{fFG\_termthru})(1 - Sx_{22\_portF}\Gamma_{portF}) \qquad (41)$$

[66]   The reverse transmission tracking error coefficient for the same proximal pair, ports F&G, where both measurement ports 103 of the proximal pair are capable of connection to the first test channel receiver 111 is measured and calculated by keeping the connection of the thru 601 between the measurement ports 103 of the proximal pair, connecting the signal generator 105 to the second one of the measurement ports 103 of the proximal pair and terminating the sampling arm 113 in a local terminating impedance 116. The first one of the measurement ports 103 of the proximal pair is terminated in the local terminating impedance 104, and the respective sampling arm 113 is connected to the first test channel receiver 111. The VNA 200 measures and stores a ratio of a transmission response over the reference signal, $A_{rFG\_termthru}/R1_{rFG\_termthru}$. The ratio is used in the transmission tracking error coefficient equation where:

49

$$\tau = (A_{rFG\_termthru} / R1_{rFG\_termthru})(1 - Sx_{22\_portG}\Gamma_{portG})$$ (42)

[67]   For purposes of illustration and with specific reference to FIGURE 11, there is shown connection diagrams for the determination of the forward and reverse transmission tracking error coefficients for the proximal pair comprising measurement ports 103_1 and 103_2. The forward transmission measurement is made by connecting the signal generator 105 to the first signal path 107. The switch network 150 is configured so that the first signal path 107 is connected to the measurement port 103_1 and the respective sampling arm 113_1 is terminated in the local sampling arm impedance 116_1. The switch network 150 is further configured so that the measurement port 103_2 is terminated in the local terminating impedance 104_2 and the sampling arm 113_2 is connected to the first test channel receiver 111. The signal generator 105 sweeps through the plurality of frequencies that define the desired frequency range and measures the ratio $A_{f12\_termthru}/R1_{f12\_termthru}$. Using equation (40) the forward transmission tracking error coefficient for the proximal pair is calculated as:

$$\tau_{12} = (A_{f12\_termthru} / R1_{f12\_termthru})(1 - Sx_{22\_port1}\Gamma_{port1})$$

[68]   The connection of the thru 601 between the

50

proximal pair and the signal transfer switch 106
configuration are maintained. With specific reference
to FIGURE 12 of the drawings, the switch network 150 is
reconfigured so that the measurement port 103_2 is
connected to the first signal path 107 and the
respective sampling arm 113_2 is terminated in the local
sampling terminating impedance 116_2. Additionally, the
switch network 150 is configured so that the
measurement port 103_1 is terminated in the local
terminating impedance 104_1 and the sampling arm 113_1 is
connected to the first test channel receiver 111. The
signal generator 105 sweeps through the plurality of
frequencies that define the desired frequency range and
measures the ratio $A_{r12\_termthru}/R1_{r12\_termthru}$. Using
equation (41) the reverse transmission tracking error
coefficient for the proximal pair is calculated as:

$$\tau_{21} = (A_{r12\_termthru} / R1_{r12\_termthru})(1 - Sx_{22\_port2}\Gamma_{port2})$$

[69] The same measurement and calculation process is
repeated for the remaining proximal pairs, which in the
illustrated embodiment is the proximal pair comprising
measurement ports 103_3 and 103_4. As one of ordinary
skill in the art appreciates, the measurements for the
proximal pair capable of connection to the second test
channel receiver 112 are carried out using the same
process, but with the second test channel receiver 112
and the second reference channel 202 as measurement

51

devices. In a multiport embodiment, the measurement and calculation process is repeated for all of the proximal pairs.

[70]   When all ten error coefficients are known for each direct, indirect, and proximal pair of measurement ports, the DUT is inserted and measured by the VNA. The resulting measured S-parameters for each direct and indirect pair of the inserted DUT are corrected according to the '511 patent to arrive at actual S-parameters for the DUT, S_{act11}, S_{act22}, S_{act12}, and S_{act21} for each direct and indirect pair. U.S. Patent Application Ser. No. 09/954,962 (herein "the '962 Patent Application"), the teachings of which are hereby incorporated by reference, teaches a process for accepting a plurality of actual S-parameter matrices, each actual S-parameter matrix representing one direct or indirect pair. Multiple direct and indirect pairs are used to represent a single multiple-port DUT. According to the teachings of the '962 Patent Application, the multiple actual S-parameters for the two-port devices that combine to represent the multi-port DUT are normalized to impedances presented to the measured ports by the multiport test set. The multiple S-parameter matrices are combined into a larger normalized single S-parameter matrix to represent the corrected and normalized S-parameters that represent the DUT as a whole. The larger S-parameter matrix is further normalized to a characteristic impedance, for example 50ohms. For purposes of the remaining

disclosure, the measured, corrected and normalized S-
parameter matrix for the DUT is referred to as the
matrix S.

[71]   Because the calibration process uses a non-zero
through calibration standard 601 and perhaps an offset
high reflect calibration standard, a reference plane
based upon the through calibration standard 601, termed
a "shifted calibration reference plane", is placed in
the center of the electrical length representing the
aggregate of the electrical lengths of any delay of the
non-zero through calibration standard 601 and any
offset of the high reflect calibration standard 301.
In on-wafer measurements, it is typical to have a zero
offset high reflect calibration standard and an unknown
non-zero through calibration standard. For coaxial
measurements, it is possible to calibrate with a zero
delay through and an offset high reflect. The
teachings herein accommodate both situations as well as
other combinations of through and high reflect
calibration standards not specifically mentioned.
FIGURE 6 of the drawings, illustrates a placement of
the shifted calibration reference plane 701. The
proper reference plane for measurement of the DUT,
however, is a reference plane that is disposed at each
measurement port that connects to the DUT, termed "the
DUT reference plane". The DUT reference plane for port
1 is shown as 702 in FIGURE 6 of the drawings. Each
measurement port 103 has a respective and similarly
situated DUT reference plane. In order to establish

the DUT reference plane for all measurements, S-
parameters for each direct and indirect pair are phase
shifted. The amount of phase shift required for the S-
parameters is calculated from a determination of the
electrical length of the non-zero through calibration
standard. The mispositioning of the reference plane may
be corrected by determining the electrical length of
the combination of the thru 601 and the offset high
reflect calibration standard 301 and adjusting
respective measured and corrected S-parameters
accordingly.

[72]   If the electrical length of the thru 601 is
unknown and the offset of the high reflect 301 is
known, the electrical length of the non-zero thru 601
between each direct and indirect pair, may be
determined. Begin with the least sum squared fit
(refer to equation (32) and accompanying text) of the
measured reflection parameter $\Gamma_{act\_reflect\_x}$ as an example
(refer to equation (40) and accompanying text) of the
measurement port for the direct or indirect pair of
interest. The slope of the function, $A_{1\_\Gamma act\_reflect\_x}$,
represents a derivative of the argument of the high
reflect calibration standard 301. The derivative of
the argument defines a change in phase with respect to
the corresponding change in frequency as a function of
frequency or $\frac{d\theta}{df}$. Any phase delay as a function of
frequency that is measured when the high reflect
calibration standard 301 is connected that cannot be

54

attributed to the high reflect calibration standard offset can be attributed to the phase delay introduced into the measurement as a result of the calibration process using the non-zero through 601. If the electrical length of the non-zero thru is known, then any phase delay that cannot be attributed to the thru calibration standard 601 can be attributed to the offset of the high reflect calibration standard 301. This phase delay attributable to the non-zero thru 601 and/or the offset reflect calibration standards, therefore, may be removed from the final DUT measurement when the electrical lengths are known. In the case of a zero offset high reflect standard, the phase shift of the high reflect standard 301 as a function of frequency is equal to the negative of the phase shift introduced by the non-zero thru 601. The aggregate electrical delay of the non-zero through and the offset of the high reflect calibration standard, represented as T in seconds, is defined as:

$$T = -\frac{d\theta}{360 df} \tag{43}$$

Accordingly, the electrical delay, T, as a function of frequency is expressed as:

$$T = \frac{1}{360} A_{1\_\Gamma act\_reflect\_x} \tag{44}$$

55

[73]   The electrical length, l, in centimeters is
calculated from the electrical delay as a function of
frequency where c is equal to 2.99793×10^{10} or the speed
of light in centimeters per second and:

$$l = cT \qquad\qquad (45)$$

The process to determine the electrical length, l, of
the aggregate offset from the non-zero thru 601 and/or
offset high reflect is repeated for each one of the
direct and indirect pairs. The electrical length may
be calculated or measured for the indirect and proximal
pairs. As a practical matter in the case of on-wafer
measurements, even if the same on-wafer calibration
standard is used, a different landing is made for each
direct and indirect pair. Because the through
calibration measurement for each direct and indirect
pair has a different landing, the electrical length of
the through calibration standard will be different for
each direct and indirect pair. Accordingly, a
different electrical length is maintained for each
direct, indirect, and proximal pair.

[74]   In many cases, a thru 601 between proximal pairs
is not commercially available on-wafer for use with
differential probes. Accordingly, the electrical

56

length of the on-wafer thru 601 for proximal pairs is
calculated instead of measured for purely practical
reasons. If an on-wafer thru calibration standard for
use with differential probes were to become available,
the electrical length between proximal pairs would be
measured and calculated as it is for the direct and
indirect pairs of measurement ports. Until then, the
electrical length is calculated from an average of the
direct and indirect pair having the proximal pair
measurement ports in common.

[75]   In an embodiment where a thru 601 may be measured
between proximal pairs, for example coaxial
measurements, the electrical length of the thru 601
between proximal pairs may be measured and calculated
as described for the direct and indirect pairs.

[76]   In an embodiment where it is not possible or
practical to measures a thru 601 between proximal
pairs, the electrical length of the through calibration
standard 601 is measured for the direct and indirect
pairs. The electrical length of each proximal pair is
then calculated from an average of the direct pair and
the indirect pair having only one port in common. As
an example, the electrical length of the thru 601
between ports 3 and 4 is the average of the electrical
length of the thru calibration standards between ports
1 and 3 and between ports 1 and 4.

[77]   For purposes of nomenclature, electrical length is
represented as "l" with a subscript that represents the

57

two ports to which it applies. Accordingly, the electrical length between measurement ports 103_1 and 103_3 is represented as "l_{13}". In the illustrated four port DUT, electrical length is determined for all through calibration standards yielding l_{13}, l_{24}, l_{14}, and l_{23} electrical lengths for the thrus 601 measured between the direct and indirect pairs. The electrical length calculation of the two remaining proximal pairs yields l_{12} and l_{34}.

[78] In order to make the appropriate calculations to yield the electrical length of the direct and indirect pairs, the measurements made for the source terminated thru are used. Specifically, for the thru 601 measured between measurement ports 103_1 and 103_3, the measurement arrays A_{f13_thru}, $R1_{f13\_thru}$, B_{f13_thru}, $R2_{f13\_thru}$, A_{r13_thru}, $R1_{r13\_thru}$, B_{r13_thru}, and $R2_{r13\_thru}$ are used to calculate the $\Gamma_{act\_reflect\_x}$ term for the first direct pair. The $\Gamma_{act\_reflect\_x}$ is used to obtain the $A_{1\Gamma\_act\_reflect\_x}$ term from equation (32) or (33) to make the electrical length determination from equations (41)-(43). A similar calculation is made for all direct and indirect pairs of the multiport configuration to determine the electrical length of each combination of the through calibration standard 601 and offset reflect.

[79] The elements of the matrix S are phase shifted according to the measured electrical length of the specific thru 601 and high reflect 301 used in the calibration process to correct the mispositioning of

the calibration reference plane. For example, in a four port DUT embodiment, the electrical length l_{13} is used to correct parameters S_{11}, S_{13}, S_{31}, and S_{33}. Similarly the electrical length l_{24} is used to correct parameters S_{22}, S_{24}, S_{42}, and S_{44}, electrical length l_{14} is used to correct parameters S_{14}, and S_{41}, electrical length l_{23} is used to correct parameters S_{23}, and S_{32}, electrical length l_{12} is used to correct parameters S_{12}, and S_{21}, and electrical length l_{34} is used to correct parameters S_{34}, and S_{43}. It is assumed that the same high reflect calibration standard 301 is used for all measurement ports 103.

[80] In a currently preferred method, the resulting measured, corrected, and normalized S-parameters are adjusted at each frequency. If the unrotated S-parameter is represented as a general complex parameter, then:

$$S = |\rho| e^{-j\theta_0} \tag{46}$$

where Θ_0 is the phase of the corrected and unrotated S-parameter. The Θ term may be represented as a component of measured phase attributable to the measured DUT, Θ_{dut}, and a component of measured phase attributable to the shifted reference plane, $\delta\Theta$, where:

$$\theta_{dut} = \theta_0 + \delta\theta \tag{47}$$

59

The length, l, in centimeters is then used to calculate
phase shift attributable to the non-zero thru
calibration standard 601 and high reflect standard as a
function frequency, f, in GHz where:

$$\delta\theta(f) = -12.0083\,f\,l \tag{48}$$

where $\delta\theta$ is determined as a function of frequency for
each electrical length represents the phase rotation
attributable to the reference plane shift. When the
electrical length and, therefore, the phase shift
attributable to the sum of the electrical delay of the
non-zero through calibration standard plus any offset
in the high reflect standard as a function of frequency
for each two-port combination is known from equation
(49), the corrected and unrotated S-parameters may be
adjusted as a function of frequency of the reference
plane for each S-parameter.

[81]   Accordingly, phase corrected S-parameters are
calculated as a function of frequency where:

$$S_{dut} = |\rho|\,e^{-j(\theta_0 + \delta\theta(f))} \tag{49}$$

The resulting s-parameters in the S_{dut} matrix represents
measured, corrected and normalized S-parameters for the

measured DUT where the measurement reference plane has been correctly placed at the DUT measurement reference plane 702.

[82]   In an alternative embodiment of an electrical length calculation for a TRL calibration process, forward and reverse measurements of the high reflect 301, line 501 and optional matched loads, and source terminated through 601 calibration standards are taken for just the direct pairs. Directivity, reflection tracking and source match as well as electrical length of the thru 601 plus any offset high reflect 301 is measured and calculated for the direct pairs of measurement ports 103. Forward and reverse measurements of the locally terminated thru calibration standard 601 are then taken for just the direct and indirect pairs of measurement ports and calculated as taught herein. Alternatively, only the direct pair is measured and transmission tracking and load match may be calculated for the indirect and proximal pairs from the teachings of the '040 Patent Application. Optionally, forward and reverse measurements of the locally terminated thru 601 may be taken for calculation of transmission tracking and load match according to the teachings herein. The S-parameters of the DUT are measured, corrected and normalized according to the teachings herein. From the error terms, the electrical length of the thru plus any offset high reflect may be calculated for the indirect and proximal pairs as follows where "n" is a first port

61

and "m" is a second port. Begin with the relationships:

$$\Gamma_{SM\_portn} = EDF_{portn} + \frac{ERF_{portn}\, \Gamma_{SA\_portn}}{1 - ESF_{portn}\, \Gamma_{SA\_portn}} \qquad (50)$$

where Γ_{SM_portn} is the measured source match for port "n", Γ_{SA_portn} is the actual source match for port "n", and EDF_{portn}, ERF_{portn}, ESF_{portn} are the calculated error coefficients for port "n" and:

$$\Gamma_{SA\_portn} = S_{11\_thru\_nm} + \frac{S_{21\_thru\_nm} S_{12\_thru\_nm}\, \Gamma_{LA\_portm}}{1 - S_{22\_thru\_nm}\, \Gamma_{LA\_portm}} \qquad (51)$$

where Γ_{LA_portm} is the actual load match for port "m" and $S_{11\_thru\_nm}$, $S_{21\_thru\_nm} S_{12\_thru\_nm}$ and $S_{22\_thru\_nm}$ are the measured S-parameters of the source terminated thru calibration standard 601. Because the thru calibration standard 601 is defined as having a perfect match, equation (51) reduces to:

$$\Gamma_{SA\_portn} = 0 + \frac{S_{21\_thru\_nm} S_{12\_thru\_nm}\, \Gamma_{LA\_portm}}{1 - 0} = S_{21\_thru\_nm} S_{12\_thru\_nm}\, \Gamma_{LA\_portm} \qquad (52)$$

and

$$\frac{\Gamma_{SA\_portn}}{\Gamma_{LA\_portm}} = S_{21\_thru\_nm} S_{12\_thru\_nm} \tag{53}$$

Because $S_{21\_thru\_nm} = S_{12\_thru\_nm}$, there are two possible solutions. Fitting the argument of the square root of $S_{21\_thru\_nm}$ to a straight line using a least sum squared fit and equation (32) or (33), the solution with a y-intercept closest to zero is the correct solution and the resulting argument of the correct solution is the length of the electrical delay between the two proximal pair measurement ports. This length is used to correct for the shifted reference plane according to equations (46)-(49) and the accompanying text.

[83] With specific reference to FIGURES 13 through 17 of the drawings, there is shown a flow chart of an embodiment of a method according to the present teachings in which measurements for the direct and indirect pairs of measurement ports 103 are taken for the high reflect calibration standard 301, the line calibration standard 401, the source terminated thru calibration standard 601 and the locally terminated thru calibration standard 601. A measurement of the locally terminated thru calibration standard 601 is taken for each proximal pairs of the measurement ports 103. The high reflect calibration standard 301 is connected 2201 to a measurement port 103 and the switch network 150 is configured for measurement 2202 by the

63

VNA 200 of a ratio of the reflection response over the
stimulus. See FIGURE 2 of the drawings. The ratio
yields a value for a reflection ratio for a number of
frequencies in a desired frequency range. The numbers
are stored in a data array where each element of the
data array holds the measured ratio at a single
frequency. The reflect calibration standard 301 is
then disconnected and reconnected 2203 to a next
measurement port, the switch network 150 is
reconfigured, and similar measurements are made and
stored in respective data arrays. The process
continues for each measurement port 103 of the VNA 200.
In a preferred embodiment, the desired frequency range
for which all measurements are taken is the same. In
this case, each element in the data arrays represents
measured results at the same frequency point along the
desired frequency range.

[84]   The flow chart of FIGURE 13 continues with the
step of connecting 2301 and configuring 2302 the switch
network 150 for termination of the line 401 at the
source 109 and measurement of the line calibration
standard 401 between a first direct or indirect pair.
The VNA 200 measures 2302 a forward direction
reflection and transmission response at the measurement
ports 103 of the direct or indirect pair at the first
and second test channel receivers 111, 112 as well as
the first and second reference channels 201, 202. The
switch network 150 is then reconfigured 2303 for the
reverse direction measurement and the VNA 200 then

64

measures 2303 a reverse direction reflection and transmission response at the measurement ports 103 of the direct pair at the first and second test channel receivers 111, 112 as well as the first and second reference channels 201, 202. Not shown in the flow chart is the connection and measurement of the matched loads 501 as shown in FIGURE 6 of the drawings to extend the calibration to the lower frequency range. A measurement of the line 401 calibration standard is performed for each direct and indirect pair.

[85] With specific reference to FIGURES 14 of the drawings, the flow chart continues with the step of connecting 2401 the thru 601 to a first direct pair of measurement ports 103. The switch network 150 is configured 2402 for forward direction measurement of the thru 601 with a termination at the source 109, and the forward direction reflection and transmission responses and the reference channel signals are measured and stored in data arrays. The switch network 150 is then reconfigured 2403 for the reverse direction measurements with the thru 601 terminated at the source 109 and the reverse direction reflection and transmission responses and the reference channel signals are measured and stored in data arrays.

[86] The thru 601 remains connected and the switch network 150 is reconfigured 2501 for a forward direction measurement, where the thru 601 is locally terminated in a local impedance 104 within the switch network 150. The forward direction reflection and

transmission responses of the locally terminated thru
601 are measured and stored as well as the reference
channel signals. The switch network 150 is then
reconfigured 2502 for a reverse direction measurement
of the locally terminated thru 601, the reverse
reflection and transmission responses and the reference
channel signals are measured and stored. The process
repeats 2503 for all N/2 direct pairs and N(N-2)/4
indirect pairs of measurement ports 103 for an N port
DUT.

[87] At this point in the process, there is sufficient
information to calculate an electrical length of the
aggregate thru/offset reflect between direct and
indirect pairs of measurement ports 103 used in the
calibration process. For purposes of process, however,
all calculations are made after all measurements are
taken.

[88] With specific reference to FIGURE 15, there is
shown an optional portion of the measurement process
wherein forward and reverse measurements of the locally
terminated thru calibration standard 601 is taken
between each proximal pair of measurement ports 103. A
user connects the thru 601 between one of the proximal
pairs 2504. The switch network 150 is then configured
2505 for a forward measurement of the locally
terminated through, measurements are taken and stored.
The switch network 150 is then configured 2506 for the
reverse measurement of the locally terminated thru 601,
measurements are taken and stored. The process repeats

for each $N(N-2)/4$ proximal pairs.

[89]   With specific reference to FIGURE 16 of the
drawings, the flow chart continues with the steps of
calculating 2705 a forward reflection tracking error
coefficient 1903 based upon a boundary condition at DC
and using the forward reflection tracking error
coefficient result, calculating 2706 a forward source
match 1902 and forward directivity 1901 error
coefficients.   The reverse reflection tracking error
coefficient 1920 is calculated 2707 also based upon a
boundary condition at DC.   Using the reverse reflection
tracking error coefficient 1906 result, the reverse
directivity 1904 and reverse source match 1905 are
determined 2708.   The method then determines 2709 the
forward and reverse load match and the forward and
reverse transmission tracking error coefficient to
arrive at ten error terms based upon the TRL
calibration.   All ten error terms are determined for
all direct and indirect pairs in a loop 2710 that
increments 2711 through the plurality of two-port
measurements.

[90]   With specific reference to FIGURE 17 of the
drawings, the process continues with optional process
paths shown as alternative paths on the flow chart.   In
one embodiment, the forward and reverse transmission
tracking error coefficients for each proximal pair are
calculated 2803 according to the teachings of the '040
Patent Application.   In an alternate embodiment, if the
locally terminated thru 601 is measured 2804 between

67

each proximal pair of measurement ports 103. The
forward and reverse transmission tracking coefficient
of each proximal pair are determined 2805 from the
measurements made. When the transmission tracking
error coefficients are determined for each proximal
pair of measurement ports 103, the process continues
with the steps of determining 2801 a type of high
reflect calibration standard 301 used in the
calibration process and calculating 2802 an electrical
length of each thru calibration standard 601 used in
the calibration process between each direct and
indirect pair. An electrical length is then typically
calculated 2806 for each proximal pair based upon an
average of the electrical length between direct and
indirect pairs having a single common measurement port.
If and when it is practical to measure a source
terminated thru 601 between proximal pairs, the
electrical length may be calculated as for the direct
pairs.

[91]   With specific reference to FIGURE 18 of the
drawings, when all of the systematic error coefficients
are determined, the DUT 101 is inserted for measurement
2902 to yield N(N-1)/2 2-port S-parameter matrices to
represent an N port DUT. The measured DUT data is then
corrected 2903 according to the teachings of the '511
Patent. As also taught in the '511 patent, the
corrected S-parameters matrices representing the
plurality of 2-port devices are combined to yield an
NxN S-parameter matrix that is corrected for the

68

systematic errors of the VNA. The corrected S-parameter matrix is then normalized to a characteristic impedance.

[92]   Using the respective electrical length determined for each thru 601 the NxN corrected and normalized S-parameters of the measured DUT are further corrected by shifting the reference plane from the shifted calibration reference plane 601 to the DUT reference plane 702 as a function of frequency. The reference plane shift operation yields a NxN S_{final} matrix, which represents the S-parameters for only the DUT after all corrections are made.

[93]   In yet another alternative embodiment of a process according to the present teachings, reflection measurements for all measurement ports are taken, and measurements are taken for the line and the source terminated through for the direct pairs only. At this point in the process, it is possible to calculate electrical length for the thru/offset between the direct pairs. Additional measurements of the locally terminated thru 601 are taken for the direct and indirect pairs of measurement ports 103. The transmission tracking and load match coefficients may be calculated from the terminated thru measurements. The characteristics of the high reflect standard are determined and the electrical length for the indirect pairs is calculated based upon equations (50) - (53). The electrical length for the proximal pairs may then be calculated based upon the average of the direct and

indirect pair having a common port. All error
coefficients and electrical lengths being determined,
the DUT is measured, corrected, normalized and a
reference plane is shifted to a DUT reference plane as
appropriate based upon the respective electrical
lengths.

[94]   A method according to the present teachings may be
performed by a computer with access to measured S-
parameter characterization data for the through-
reflect-line calibration standards as well as the S-
parameter characterization data for the DUT. The VNA
performs the measurements and either stores the
resulting data arrays on removable media or may be
connected to a computer via a communications bus for
storage on some other form of storage media. A method
according to the present teachings may also be
performed by the computational processor that is
typically part of the VNA.   Specifically, it is not
necessary to know the type of high reflect calibration
standard 301 used in the calibration process and it is
not necessary to know the electrical length of the thru
calibration standard 601. If a phase offset of a
reflect calibration standard is known, a method
according to the present teachings is able to measure
and calculate the electrical length of the thru
calibration standard 601 rather than relying on
manufacturer's data. If the electrical length of the
thru calibration standard is known, a method according
to the present teachings calculates the phase offset of

70

the reflect calibration standard. The calculated electrical length or phase offset is more accurate that manufacturer supplied data and, therefore, provides for a more accurate calculation of the error artifacts for correction of measured data. This is especially advantageous when calibrating for on-wafer measurements where a repeatable thru calibration standard is difficult to obtain and when using a calibration standard having characteristics that may have changed slightly due to environmental conditions and repeated use. In addition, the present teachings recognize that calibration using a non-zero through places a transmission reference plane at a position different from the reflection measurements. A method or apparatus according to the present teachings is able to calculate the error attributable to use of a non-repeatable and non-zero through. The method or apparatus according to the present teachings is also able to make further corrections to what was considered corrected data in the prior art to place the transmission measurement reference plane at a same point as a position of the reflection measurement reference plane. The more accurate through calibration standard combined with the additional correction for the shifted measurement reference plane provides a more accurate measurement of the frequency response attributable to only the device under test and not the connection environment with which the device under test is connected to the measurement equipment.

71